


R11 CONCTACT CLEANER WITH ANTIOXIDANT FORMULA (200ML)



SKU: 101392A



DUE-CI ELECTRONIC R-11 – CONTACT CLEANER

R-11 Contact cleaner has been studied for dissolving and removing oxidation from any electrical contact: electrical and electromechanical slide contacts, switches, push buttons, commutators, plugs, sockets, keyboards... etc.

Thanks to a special chemical additive, **prevents a new oxidation process** in the treated parts.

It eliminates the creaking of potentiometers.

It assures a deep and effective cleaning in linear and sliding contacts, without any risk for the support plastic materials.

Specifications

- Manufacturer: **DUE-CI Electronic**
- Packaging: **200 ml spray can**
- OZONE SAFE
- CFC AND HCFC FREE
- CHLORINATED SOLVENTS FREE
- SAFE FOR MOST PLASTICS
- HIGHLY PROTECTIVE



- LUBRICATING AND ANTI-CORROSIVE PROPERTIES.

PRODUCT IDENTIFIER IN THE SAFETY DATA SHEET:

Product name: **R-11 Contact Cleaner Plus ml.200** – Codice: **R11Plus**

LABEL ELEMENTS:

Hazard labelling pursuant to EC Regulation 1272/2008 (CLP) and subsequent amendments and supplements.

Hazard pictograms:



Danger. Extremely flammable aerosol. Pressurized container: may burst if heated. Causes serious eye irritation. Causes skin irritation. May cause drowsiness or dizziness. Harmful to aquatic life with long lasting effects.

Precautionary statements: Keep away from heat / sparks / open flames / hot surfaces. No smoking - Do not spray on an open flame or other ignition source - Do not pierce or burn, even after use - Avoid breathing spray - Protect from sunlight. Do not expose to temperatures exceeding 50°C / 122°F. Wear protective gloves/protective clothing/eye protection/face protection.

Contains: 2-PROPANOL - C6 isoalkaline hydrocarbons < 5% n-Hexane - ETHYL ACETATE.

Nominal quantity: 200ml.

DETAILS OF THE SUPPLIER OF THE SAFETY DATA SHEET:

DUE-CI ELECTRONIC Srl – Strada del Casalino 11, 37127 – Verona (VR) - ITALY

Tel. +39 045 916251 – www.duecielectronic.it