

## R11 CONCTACT CLEANER WITH ANTIOXIDANT FORMULA (200ML)



**SKU:** 101392A



## **DUE-CI ELECTRONIC R-11 - CONTACT CLEANER**

**R-11 Contact cleaner has been studied for dissolving and removing oxidation from any electrical contact**: electrical and electromechanical slide contacts, switches, push buttons, commutators, plugs, sockets, keyboards... etc. Thanks to a special chemical additive, **prevents a new oxidation process** in the treated parts.

It eliminates the creaking of potentiometers.

It assures a deep and effective cleaning in linear and sliding contacts, without any risk for the support plastic materials.

## **Specifications**

- Manufacturer: DUE-CI Electronic
- Packaging: 200 ml spray can
- OZONE SAFE
- CFC AND HCFC FREE
- CHLORINATED SOLVENTS FREE
- SAFE FOR MOST PLASTICS
- HIGHLY PROTECTIVE



LUBRICATING AND ANTI-CORROSIVE PROPERTIES.

PRODUCT IDENTIFIER IN THE SAFETY DATA SHEET:

Product name: R-11 Contact Cleaner Plus ml.200 - Codice: R11Plus

## LABEL ELEMENTS:

Hazard labelling pursuant to EC Regulation 1272/2008 (CLP) and subsequent amendments and supplements. Hazard pictograms:





Danger. Extremely flammable aerosol. Pressurized container: may burst if heated. Causes serious eye irritation. Causes skin irritation. May cause drowsiness or dizziness. Harmful to aquatic life with long lasting effects.

Precautionary statements: Keep away from heat / sparks / open flames / hot surfaces. No smoking - Do not spray on an open flame or other ignition source - Do not pierce or burn, even after use - Avoid breathing spray - Protect from sunlight. Do no expose to temperatures exceeding  $50^{\circ}$ C /  $122^{\circ}$ F. Wear protective gloves/protective clothing/eye protection/face protection.

Contains: 2-PROPANOL - C6 isoalkaline hydrocarbons < 5% n-Hexane - ETHYL ACETATE.

Nominal quantity: 200ml.

DETAILS OF THE SUPPLIER OF THE SAFETY DATA SHEET: **DUE-CI ELECTRONIC SrI** – Strada del Casalino 11, 37127 – Verona (VR) - ITALY

Tel. +39 045 916251 – www.duecielectronic.it